

## 9.0 Accessories

Beacon 110	LEL Direct	13 hours
Beacon 110	Toxic or Oxygen (4 - 20 mA or Direct)	19 hours
Beacon 110	35-3000RK Sample Draw Detector	4 hours
Beacon 110	GD-K7D2-24V Sample Draw Detector	8 hours
Beacon 200	Two Channels LEL 4 - 20 mA Transmitter	4.5 hours
Beacon 200	Two Channels LEL Direct	4.5 hours
Beacon 200	Two Channels Toxic or Oxygen (4 - 20 mA or Direct)	10 hours
Beacon 200	Two Channels 35-3000RK Sample Draw Detector	2 hours
Beacon 200	Two Channels GD-K7D2-24V Sample Draw Detector	2.5 hours
<b>Battery 49-8104RK Backup</b>		
<b>Controller</b>	<b>Controller Detector Configurations</b>	<b>Typical Runtime</b>
Beacon 200	Two Channels LEL 4 - 20 mA Transmitter	40 hours
Beacon 200	Two Channels LEL Direct	40 hours
Beacon 200	Two Channels Toxic or Oxygen (4 - 20 mA or Direct)	90 hours
Beacon 200	Two Channels 35-3000RK Sample Draw Detector	18 hours
Beacon 200	Two Channels GD-K7D2-24V Sample Draw Detector	22 hours
Beacon 800	Eight Channels LEL 4 - 20 mA Transmitter	18 hours
Beacon 800	Eight Channels Toxic or Oxygen 4 - 20 mA Transmitter	60 hours
Beacon 800	Eight Channels 35-3000RK Sample Draw Detector	4 hours
Beacon 800	Eight Channels GD-K7D2-24V Sample Draw Detector	5 hours